

CASAMBI PIR motion and brightness sensor for outdoor wall mounting

Order number: 5351

- PIR motion and brightness sensor for convenient operation of luminaires via CASAMBI app
- Mounting height: max. 17m (ceiling mounting) for wall mounting recommended height 1 to 2.2m
- Extra sensitive motion sensor with extended detection range: 10-20m see graphics
- Power supply via 220V mains
- Complete control via CASAMBI App:
 - presence/absence detection
 - ambient light dependent control of luminaires/scenes
 - Light duration and fade-in/fade-out times

Assign the desired scenes to the sensor via app

- Automatically switch luminaires/devices on and off after motion detection
- Integrated brightness sensor - light intensity as required
- Absence setting - change dimming level in case of absence
- Day and night setting - individual light at specific times when motion is detected
- The motion detector can also be activated/deactivated by switch or timer

Input voltage: 220 - 240 V AC; Inrush current in A: 0; Warranty in years: 2; Housing material: Polycarbonate; Radio frequency: 2,4;
Mounting location: Indoor + Outdoor; ETIM Gruppen-ID: ECO02556; Pulse duration in µs: 0; BEG funding: Only relevant in Germany; Dreh-/Schwenkbar: not swivelling; Adjustability: Not adjustable; Colour: White
width: 60mm