

PRODUCT NO. 5277

DOTLUX LED Wireless Receiver/DimmerTuya & Fusion Triac Receiver 1.5A 1Channel 100 - 240V AC



to the product page



- WiFi Dotlux Fusion Technology Push AC phase angle dimmer, 1 channel output.
- For dimming and switching single color dimmable LED lamps or halogen lamps.
- Tuya APP cloud control, supports power on/off, brightness adjustment, delayed light on/off, timer, scene and music playback function.
- Voice control, supports Amazon ECHO and smart speakers.
- Dimming type adjustable by dip switch, phase cut/prime cut.
- minimum brightness can be preset via push button
- additional wired push button control input
- Each dimming module can also work as a TUYA to Fusion converter
- Via the Tuya APP, one or more LED controllers or drivers can be controlled synchronously
- Easy installation in standard wall junction boxes behind a push button
- Overheating/overload protection, automatic recovery
- Inrush current of connected LED luminaires/ballasts must not exceed 130A

SUCCESSION ARTICLE	-	PROTECTION CLASS (IP)	IP20
WEIGHT IN KG	0.048	INPUT VOLTAGE SPAN	100-240 V AC
		WARRANTY IN YEARS	3
		CONTROL METHOD	Leading edge/trailing edge phase control
		INPUT VOLTAGE RANGE LUMINAIRE	100-240 V AC
		ETIM GRUPPEN-ID	EC002924
		SUITABLE FOR DOTLUX FUSION	Yes
		SUITABLE FOR TUYA	Yes
		BEG FUNDING	Only relevant in Germany
Dimensions			
width: 52mm			
height: 26mm			
length: 52mm			