

DOTLUX LED Wireless Receiver/DimmerTuya & Fusion Triac Receiver 1.5A 1Channel 100 - 240V AC

Order number: 5277

- WiFi Dotlux Fusion Technology Push AC phase angle dimmer, 1 channel output.
- For dimming and switching single color dimmable LED lamps or halogen lamps.
- Tuya APP cloud control, supports power on/off, brightness adjustment, delayed light on/off, timer, scene and music playback function.
- Voice control, supports Amazon ECHO and smart speakers.
- Dimming type adjustable by dip switch, phase cut/prime cut.
- minimum brightness can be preset via push button
- additional wired push button control input
- Each dimming module can also work as a TUYA to Fusion converter
- Via the Tuya APP, one or more LED controllers or drivers can be controlled synchronously
- Easy installation in standard wall junction boxes behind a push button
- Overheating/overload protection, automatic recovery
- Inrush current of connected LED luminaires/ballasts must not exceed 130A

protection class (IP): IP20; Input voltage span: 100-240 V AC; Warranty in years: 3; Control method: Leading edge/trailing edge phase control; Input voltage range luminaire: 100-240 V AC; ETIM Gruppen-ID: EC002924; suitable for Dotlux Fusion: Yes; suitable for Tuya: Yes; BEG funding: Only relevant in Germany
width: 52mm