

PRODUCT NO. 5115

CASAMBI PWM dimmer 12-24V 4-channel max. 144W



to the product page

- PWM dimmer with 4 channels for 12V or 24V for convenient operation of luminaires via CASAMBI App
- the dimmer is mounted between the non-dimmable 12-24 VDC control gear and the constant voltage product
- suitable for 1-color strips, COLORselect strips, RGB and RGBW strips
- the max. output current is 6A, this can be freely distributed to the channels 1-4
- protected against: overload, overcurrent and short circuit
- different pre-installed profiles are selectable in CASAMBI App
- compatible with sensor (art. no. 5117), radio remote control (art. no. 5120) and wall switch (art. no. 5121)
- Complete control via CASAMBI App:
- Control of brightness and light color
- Configuration of luminaires and luminaire networks
- creation of scenes and animations (color gradients)
- intelligent timer and gallery functions

SUCCESSION ARTICLE	-
WEIGHT IN KG	0.023
POWER CONSUMPTION IN WATTS	max. 144W bei 24V

PROTECTION CLASS (IP)	IP20
INRUSH CURRENT IN A	0
TC TEMPERATURE IN °C	75
COLOUR CHANNELS	RGBW
OUTPUT VOLTAGE	12 - 24 DC
RADIO FREQUENCY	2,4 GHz
ENERGY EFFICIENCY CLASS ACCORDING TO EU REGULATION 2019/2015	not required
ETIM GRUPPEN-ID	EC002924
PULSE DURATION IN µS	0
BEG FUNDING	Only relevant in Germany

Dimensions

length: 73mm
width: 30mm

height: 18mm