

PRODUCT NO. 5122

CASAMBI interface 1-10V/DALI for individual device control



to the product page

- Interface for convenient operation of DALI or 1-10V luminaires via CASAMBI app (max. 2 DALI devices)
- Suitable for retrofitting individual DALI or 1-10V luminaires (individual luminaire control)
- suitable for integrating a conventional push-button or a DALI sensor into the CASAMBI world
- compatible with sensor (item no. 5117), radio remote control (item no. 5120) and wall switch (item no. 5121)

- Complete control via CASAMBI app:
- Control of brightness and light color
- Configuration of luminaires and luminaire networks
- Creating scenes and animations (color gradients)
- Intelligent timer and gallery functions

- Sends to the DALI addresses: 0, 1, 2, 3 (depending on the channels) Addressing cannot be adjusted via the app. Devices must have these addresses preset.
- Change fixture before coupling to the network: Change profile

SUCCESSION ARTICLE	-	PROTECTION CLASS (IP)	IP20
WEIGHT IN KG	0.048	INPUT VOLTAGE	220 - 240 V AC
		INRUSH CURRENT IN A	0
		TC TEMPERATURE IN °C	70
		INPUT VOLTAGE SPAN	220-240 V AC
Dimensions		HOUSING MATERIAL	Plastic
		RADIO FREQUENCY	2,4 GHz
		INPUT VOLTAGE RANGE LUMINAIRE	220-240 V AC
length: 57mm		ENERGY EFFICIENCY CLASS ACCORDING TO EU REGULATION 2019/2015	not required
width: 36mm		ETIM GRUPPEN-ID	EC002710
height: 23mm		DIMMING 1-10 V	Yes
		DIMMING MANUFACTURER'S PROPRIETARY SYSTEM	Yes
		DIMMING RF	Yes
		NO DIM FUNCTION	No
		PULSE DURATION IN µS	0
		BEG FUNDING	Only relevant in Germany