

PRODUCT NO. 5350

CASAMBI switching relay / switching actuator for switching 220V consumers



to the product page

This CASAMBI relay allows lights and other consumers to be switched on and off via smartphone

- Complete control via CASAMBI App:
- Selectable operating modes/profiles
- Wireless control via app, wall switch and motion detector
- Automatic switching on and off according to times, days of the week, date or sun times
- Integration in scenes and animations

Simply select the appropriate profile via the app:  
-Switch Actuator (switch actuator for lights)  
-Push Actuator (push actuator: remains switched on as long as it is pushed)

LED lamps and transformers max.6A (1500W)  
Incandescent/halogen lamps 10A (2300W)  
Fans 1A (230W)  
Inrush current max :120A, 20ms

|                            |       |   |                |
|----------------------------|-------|---|----------------|
| SUCCESSION ARTICLE         | -     | PROTECTION CLASS (IP)                     | IP40           |
| WEIGHT IN KG               | 0.109 | INPUT VOLTAGE                             | 100 - 240 V AC |
| POWER CONSUMPTION IN WATTS | <0,5  | OUTPUT CURRENT IN A                       | 10             |
|                            |       | INRUSH CURRENT IN A                       | 0              |
|                            |       | PROTECTION CLASS                          | II             |
|                            |       | OUTPUT VOLTAGE                            | potential-free |
|                            |       | WARRANTY IN YEARS                         | 2              |
|                            |       | MOUNTING LOCATION                         | Indoor         |
|                            |       | ETIM GRUPPEN-ID                           | EC002710       |
|                            |       | DIMMING 1-10 V                            | No             |
|                            |       | DIMMING DALI                              | No             |
|                            |       | DIMMING DMX                               | No             |
|                            |       | DIMMING DSI                               | No             |
|                            |       | DIMMING POTENTIOMETER (INTEGRATED)        | No             |
|                            |       | DIMMING LINESWITCH                        | No             |
|                            |       | DIMMING MANUFACTURER'S PROPRIETARY SYSTEM | No             |
|                            |       | DIMMING MAINS VOLTAGE MODULATION          | No             |
|                            |       | DIMMING PHASE CUT-OFF                     | No             |
|                            |       | DIMMING PROGRAMMABLE                      | No             |
|                            |       | DIMMING WITH PUSH-BUTTON                  | No             |
|                            |       | NO DIM FUNCTION                           | Yes            |
|                            |       | COMPATIBLE WITH CASAMBI                   | Yes            |
|                            |       | COMPATIBLE WITH APPLE HOMEKIT             | No             |

Dimensions

length: 120mm  
width: 50mm  
height: 33mm

|  |                          |
|--|--------------------------|
| <b>COMPATIBLE WITH GOOGLE ASSISTANT</b>    | No                       |
| <b>COMPATIBLE WITH AMAZON ALEXA</b>        | No                       |
| <b>SUITABLE FOR OUTDOOR USE</b>            | No                       |
| <b>HOUSING</b>                             | Plastic housing          |
| <b>DIMMING PHASE CUT-ON</b>                | No                       |
| <b>PULSE DURATION IN <math>\mu</math>S</b> | 0                        |
| <b>BEG FUNDING</b>                         | Only relevant in Germany |