


PRODUCT NO. 5351

CASAMBI PIR motion and brightness sensor for outdoor wall mounting



to the product page

- PIR motion and brightness sensor for convenient operation of luminaires via CASAMBI app
- Mounting height: max. 17m (ceiling mounting) for wall mounting recommended height 1 to 2.2m
- Extra sensitive motion sensor with extended detection range: 10-20m see graphics
- Power supply via 220V mains
- Complete control via CASAMBI App:
- presence/absence detection
- ambient light dependent control of luminaires/scenes
- Light duration and fade-in/fade-out times

Assign the desired scenes to the sensor via app

- Automatically switch luminaires/devices on and off after motion detection
- Integrated brightness sensor - light intensity as required
- Absence setting - change dimming level in case of absence
- Day and night setting - individual light at specific times when motion is detected
- The motion detector can also be activated/deactivated by switch or timer

SUCCESSION ARTICLE	-	INPUT VOLTAGE	220 - 240 V AC
WEIGHT IN KG	0.107	INRUSH CURRENT IN A	0
		WARRANTY IN YEARS	2
		HOUSING MATERIAL	Polycarbonate
		RADIO FREQUENCY	2,4
		MOUNTING LOCATION	Indoor + Outdoor
		ETIM GRUPPEN-ID	EC002556
		PULSE DURATION IN µS	0
		BEG FUNDING	Only relevant in Germany
		DREH- /SCHWENKBAR	not swivelling
		ADJUSTABILITY	Not adjustable
		COLOUR	White

Dimensions

height: 37mm  
length: 75mm  
width: 60mm