

PRODUCT NO. 5364

**DOTLUX Emergency lighting module for high bay floodlight 1-10V max.200W**



to the product page

By connecting a 1-10V dimmable LED light, it can be used in both normal and emergency mode.

In the event of a power failure, the device automatically switches to emergency mode and dims the connected light to 10% output with the 1-10V interface

The emergency power depends on the power of the connected luminaire.

As a rule, 10% of the original luminaire output

The lower the output of the luminaire, the lower the emergency power output. The lower the output of the luminaire, the longer the emergency power operating time. **Limited to 200W - Can only be operated with luminaires up to MAX.200W.** Example emergency power output: With a 100W luminaire, the output in emergency power mode is approx. 10W and lasts approx. 180 minutes. With 200W correspondingly 20W and approx. 90min.

SUCCESION ARTICLE	-	INPUT VOLTAGE	220 - 240 V AC
WEIGHT IN KG	2.43	WARRANTY IN YEARS	3
POWER CONSUMPTION IN WATTS	max20W DC	SELF-TEST	Automatic self-test
		ETIM GRUPPEN-ID	EC000471
		BEG FUNDING	Only relevant in Germany

**Dimensions**

**length:** 427mm

**width:** 133mm

**height:** 75mm