

PRODUCT NO. 4343-2

**DOTLUX EMERGENCY CURRENT ACCU KIT EMERGENCY LIGHT BATTERY 5W 10-90V Self-test constant power (3h) for constant current operated LED lights LiFePO4 7.3V**



to the product page

- In the event of a power failure, the kit provides emergency lighting for constant current-operated LED lights, which are then powered by the internal battery
- If the light is switched off and the mains power fails, emergency power operation also starts
- The emergency power supply AKKU-KIT is primarily designed for retrofitting continuous-row lighting systems from the DOTLUX range, e.g. linear luminaires
- Can be used universally for all LED luminaires with external ballasts with an operating voltage of 10-90 V DC.
- The emergency power supply AKKU-KIT includes an operating status LED with installation socket and a test switch for external installation
- The AKKU-KIT does not replace the power supply unit of the LED light. The AKKU-KIT must be ordered in addition to the power supply unit.
- Automatic self-test function
- Temperature resistant from -20 to 55°C

|                            |        |
|----------------------------|--------|
| SUCCESION ARTICLE          | -      |
| PREDECESSOR ARTICLE        | 4343-1 |
| WEIGHT IN KG               | 0.276  |
| POWER CONSUMPTION IN WATTS | 5W     |

|                               |                          |
|-------------------------------|--------------------------|
| INPUT VOLTAGE                 | 220 - 240 V AC           |
| BATTERY RUNTIME               | 3h                       |
| PROTECTION CLASS              | II                       |
| INPUT VOLTAGE SPAN            | 10-90V                   |
| INPUT VOLTAGE RANGE LUMINAIRE | 10-90V                   |
| ETIM GRUPPEN-ID               | EC000471                 |
| BEG FUNDING                   | Only relevant in Germany |
| LAMP TYPE                     | Other                    |

Dimensions

width: 30mm

height: 21mm

length: 158mm