

PRODUCT NO. 3923-2

**DOTLUX EMERGENCY CURRENT AKKU-KITexit 1.9W/0.8W constant power 3/8h for constant current operated LED lights with ext. test button LifePO4 6.4V with self-test**



to the product page



- In the event of a power failure, the kit provides emergency lighting for constant current-operated LED lights, which are then powered by the internal battery
- Emergency power operation also starts when the light is switched off and the mains power fails
- Can be used universally for all LED luminaires with external ballasts with an operating voltage of 10-90 V DC
- The AKKU-KITexit emergency power supply is supplied with an operating status LED with installation socket and a test switch for external installation
- The AKKU-KITexit does not replace the power supply unit of the LED light. The AKKU-KITexit must be ordered in addition to the power supply unit.
- Automatic self-test
- The AKKU-KIT can be set to different levels: 0.8@8H / 1.9W@3H
- Consumption in charging mode 3Watt
- Consumption in standby mode less than 0.5Watt

SUCCESION ARTICLE	-
PREDECESSOR ARTICLE	3923-1, 5806
WEIGHT IN KG	0.27
POWER CONSUMPTION IN WATTS	0,8 / 1,9

INPUT VOLTAGE	220 - 240 V AC
BATTERY RUNTIME	8h at 0.8W
PROTECTION CLASS	II
SUITED FOR EMERGENCY LIGHTING	yes
INPUT VOLTAGE SPAN	220-240
WARRANTY IN YEARS	3
CAPACITIY OF BATTERY IN MAH	6000
INPUT VOLTAGE RANGE LUMINAIRE	220-240
SELF-TEST	Automatic self-test
ETIM GRUPPEN-ID	EC000471
SUITABLE FOR EMERGENCY LIGHTING	Yes
BEG FUNDING	Only relevant in Germany
LAMP TYPE	Other

**Dimensions**

**height:** 25mm  
**length:** 199mm  
**width:** 55mm