

PRODUCT NO. 5806

DOTLUX EMERGENCY CURRENT AKKU-KITexit 1.8W constant power 3h for constant current operated LED lights with ext. test button LiFePO4 6.4V with self-test



to the product page



- In the event of a power failure, the kit provides emergency lighting for constant current-operated LED lights, which are then powered by the internal battery
- Emergency power operation also starts when the light is switched off and the mains power fails
- Can be used universally for all LED luminaires with external ballasts with an operating voltage of 10-90 V DC
- The AKKU-KITexit emergency power supply is supplied with an operating status LED with installation socket and a test switch for external installation
- The AKKU-KITexit does not replace the power supply unit of the LED light. The AKKU-KITexit must be ordered in addition to the power supply unit.
- Automatic self-test
- The AKKU-KIT can be set to different levels: 1.8W@3H / 2.9W@2H / 3.5W@1.5H
- Consumption in charging mode 2.5Watt
- Consumption in standby mode less than 0.5Watt

SUCCESSION ARTICLE	-	INPUT VOLTAGE	220 - 240 V AC
WEIGHT IN KG	0.27	INRUSH CURRENT IN A	0
POWER CONSUMPTION IN WATTS	1,8 / 2,9 / 3,5	BATTERY RUNTIME	3h
		TC TEMPERATURE IN °C	60
		PROTECTION CLASS	II
		BATTERY-TYPE	-
		WARRANTY IN YEARS	3
		SELF-TEST	Automatic self-test
		ETIM GRUPPEN-ID	EC000471
		PULSE DURATION IN µS	0
		BEG FUNDING	Only relevant in Germany
		LAMP TYPE	Other
Dimensions			
length:	199mm		
width:	55mm		
height:	25mm		