

**CASAMBI switching relay / switching actuator for switching 220V consumers**

Order number: 5350

This CASAMBI relay allows lights and other consumers to be switched on and off via smartphone

- Complete control via CASAMBI App:
- Selectable operating modes/profiles
- Wireless control via app, wall switch and motion detector
- Automatic switching on and off according to times, days of the week, date or sun times
- Integration in scenes and animations

Simply select the appropriate profile via the app:

- Switch Actuator (switch actuator for lights)
- Push Actuator (push actuator: remains switched on as long as it is pushed)

LED lamps and transformers max.6A (1500W)

Incandescent/halogen lamps 10A (2300W)

Fans 1A (230W)

Inrush current max :120A, 20ms

Power consumption in watts: <0,5; protection class (IP): IP40; Input voltage: 100 - 240 V AC; Output current in A: 10; Inrush current in A: 0; Protection class: II; Output voltage: potential-free; Warranty in years: 2; Mounting location: Indoor; ETIM Gruppen-ID: EC002710; Dimming 1-10 V: No; Dimming DALI: No; Dimming DMX: No; Dimming DSI: No; Dimming potentiometer (integrated): No; Dimming LineSwitch: No; Dimming manufacturer's proprietary system: No; Dimming mains voltage modulation: No; Dimming phase cut-off: No; Dimming programmable: No; Dimming with push-button: No; No dim function: Yes; Compatible with Casambi: Yes; Compatible with Apple HomeKit: No; Compatible with Google Assistant: No; Compatible with Amazon Alexa: No; Suitable for outdoor use: No; Housing: Plastic housing; Dimming phase cut-on: No; Pulse duration in  $\mu$ s: 0; BEG funding: Only relevant in Germany  
width: 50mm