

PRODUCT NO. 4343-2-B-Ware

**DOTLUX NOTSTROM-AKKU-KIT NOTLICHTBAUSTEIN 5W 10-90V Selbsttest Konstantleistung (3h)  
für konstantstrombetriebene LED-Leuchten LiFePO4 6,4V**



to the product page

- In the event of a power failure, the kit provides emergency lighting for constant current-operated LED lights, which are then powered by the internal battery
- If the light is switched off and the mains power fails, emergency power operation also starts
- The emergency power supply AKKU-KIT is primarily designed for retrofitting continuous-row lighting systems from the DOTLUX range, e.g. linear luminaires
- Can be used universally for all LED luminaires with external ballasts with an operating voltage of 10-90 V DC.
- The emergency power supply AKKU-KIT includes an operating status LED with installation socket and a test switch for external installation
- The AKKU-KIT does not replace the power supply unit of the LED light. The AKKU-KIT must be ordered in addition to the power supply unit.
- Automatic self-test function
- Temperature resistant from -20 to 55°C

<b>PRODUCT GROUP</b>	EC000471_Notlichtbaustein		
<b>PREDECESSOR ARTICLE</b>	4343-1	<b>INPUT VOLTAGE</b>	220 - 240 AC
<b>WEIGHT IN KG</b>	0.28	<b>BATTERY RUNTIME</b>	3h
<b>POWER CONSUMPTION IN WATTS</b>	5	<b>PROTECTION CLASS</b>	II
		<b>SUITED FOR EMERGENCY LIGHTING</b>	yes
		<b>INPUT VOLTAGE SPAN</b>	10-90
		<b>WARRANTY IN YEARS</b>	0
		<b>INPUT VOLTAGE RANGE LUMINAIRE</b>	10-90
<b>Dimensions</b>		<b>SELF-TEST</b>	Automatic self-test
<b>length:</b> 158mm		<b>SUITABLE FOR EMERGENCY LIGHTING</b>	Yes
<b>width:</b> 30mm		<b>LAMP TYPE</b>	-
<b>height:</b> 21mm		<b>BEG FUNDING</b>	Only relevant in Germany
		<b>DIAMETER IN MM</b>	0
		<b>ABMESSUNGEN BREITE MM</b>	30
		<b>ABMESSUNGEN HÖHE MM</b>	21
		<b>NOMINAL VOLTAGE IN V</b>	6,4