

PRODUCT NO. 2830

**DOTLUX Netzteil für DOTLUX LED-Downlight CIRCLE 20W (Art. 2827) notstromtauglich 500mA IP20 Stecker**



to the product page

|                            |      |
|----------------------------|------|
| SUCCESSION ARTICLE         | 4330 |
| WEIGHT IN KG               | 0.08 |
| POWER CONSUMPTION IN WATTS | 20   |

Dimensions

length: 119mm  
width: 40mm  
height: 27mm

|                                           |                   |
|-------------------------------------------|-------------------|
| PROTECTION CLASS (IP)                     | IP40              |
| INPUT VOLTAGE                             | 176 - 240 V AC/DC |
| OUTPUT CURRENT IN A                       | 0,5               |
| POWER FACTOR                              | 0,9               |
| TC TEMPERATURE IN °C                      | 80                |
| PROTECTION CLASS                          | I                 |
| SUITED FOR EMERGENCY LIGHTING             | yes               |
| OUTPUT VOLTAGE                            | 27 - 42 DC        |
| INPUT VOLTAGE SPAN                        | 100-240 V AC      |
| WARRANTY IN YEARS                         | 5                 |
| INPUT VOLTAGE RANGE LUMINAIRE             | 100-240 V AC      |
| ETIM GRUPPEN-ID                           | EC002710          |
| DIMMING 0-10 V                            | No                |
| DIMMING 1-10 V                            | No                |
| DIMMING DALI                              | No                |
| DIMMING DMX                               | No                |
| DIMMING DSI                               | No                |
| DIMMING POTENTIOMETER (INTEGRATED)        | No                |
| DIMMING LINESWITCH                        | No                |
| DIMMING MANUFACTURER'S PROPRIETARY SYSTEM | No                |
| DIMMING MAINS VOLTAGE MODULATION          | No                |
| DIMMING PHASE CUT-OFF                     | No                |
| DIMMING PROGRAMMABLE                      | No                |

|                                        |     |
|----------------------------------------|-----|
| <b>DIMMING RF</b>                      | No  |
| <b>DIMMING SINE WAVE REDUCTION</b>     | No  |
| <b>DIMMING TOUCH AND DIM</b>           | No  |
| <b>DIMMING ZIGBEE</b>                  | No  |
| <b>DIMMING WITH PUSH-BUTTON</b>        | No  |
| <b>NO DIM FUNCTION</b>                 | Yes |
| <b>SUITABLE FOR EMERGENCY LIGHTING</b> | Yes |
| <b>DIMMING PHASE CUT-ON</b>            | No  |
| <b>DIMMING GPRS</b>                    | No  |