

PRODUCT NO. 5069

**CASAMBI 1-channel LED power supply unit CV 24V DC 1-100W 0.42-4.2A dimmable**



to the product page

- Dimmable constant voltage power supply 24V DC max 100W
- Dimmable via CASAMBI APP

<b>PRODUCT GROUP</b>	EC002710_LED-Betriebsgerät	<b>PROTECTION CLASS (IP)</b>	IP20
<b>SUCCESSION ARTICLE</b>	-	<b>INPUT VOLTAGE</b>	176 - 240 AC/DC
<b>WEIGHT IN KG</b>	0.25	<b>POWER FACTOR</b>	0,99
<b>POWER CONSUMPTION IN WATTS</b>	100	<b>INRUSH CURRENT IN A</b>	0
		<b>TC TEMPERATURE IN °C</b>	75
		<b>SUITED FOR EMERGENCY LIGHTING</b>	yes
		<b>OUTPUT VOLTAGE</b>	24 DC
<b>Dimensions</b>		<b>INPUT VOLTAGE SPAN</b>	198-264 AC / 176-280 DC
<b>length:</b> 295mm		<b>WARRANTY IN YEARS</b>	2
<b>width:</b> 43mm		<b>DIMMING WITHOUT DIMMER</b>	No
<b>height:</b> 30mm		<b>INPUT VOLTAGE RANGE LUMINAIRE</b>	198-264 AC / 176-280 DC
		<b>DIMMING 0-10 V</b>	No
		<b>DIMMING 1-10 V</b>	No
		<b>DIMMING DALI</b>	No
		<b>DIMMING DMX</b>	No
		<b>DIMMING DSI</b>	No
		<b>DIMMING POTENTIOMETER (INTEGRATED)</b>	No
		<b>DIMMING LINESWITCH</b>	No
		<b>DIMMING MANUFACTURER'S PROPRIETARY SYSTEM</b>	No
		<b>DIMMING MAINS VOLTAGE MODULATION</b>	No
		<b>DIMMING PHASE CUT-OFF</b>	No
		<b>DIMMING PROGRAMMABLE</b>	No
		<b>DIMMING RF</b>	No

<b>DIMMING SINE WAVE REDUCTION</b>	No
<b>DIMMING TOUCH AND DIM</b>	No
<b>DIMMING ZIGBEE</b>	No
<b>DIMMING WITH PUSH-BUTTON</b>	No
<b>NO DIM FUNCTION</b>	No
<b>SUITABLE FOR EMERGENCY LIGHTING</b>	Yes
<b>OPERATION BY BLUETOOTH</b>	No
<b>COMPATIBLE WITH CASAMBI</b>	Yes
<b>COMPATIBLE WITH APPLE HOMEKIT</b>	No
<b>COMPATIBLE WITH GOOGLE ASSISTANT</b>	No
<b>COMPATIBLE WITH AMAZON ALEXA</b>	No
<b>MODEL</b>	-
<b>SUITABLE FOR OUTDOOR USE</b>	No
<b>HOUSING</b>	Plastic housing
<b>DIMMING PHASE CUT-ON</b>	No
<b>DIMMING GPRS</b>	No
<b>PULSE DURATION IN <math>\mu</math>S</b>	0
<b>BEG FUNDING</b>	Only relevant in Germany
<b>ELDAS-NR.</b>	941934169
Dimension Length in mm	
<b>DIAMETER IN MM</b>	0
<b>RATED AMBIENT TEMPERATURE ACCORDING TO IEC62722-2-1 IN °C</b>	-25-50
<b>ABMESSUNGEN BREITE MM</b>	43
<b>ABMESSUNGEN HÖHE MM</b>	30
Ausgangsstrom in A	