

PRODUCT NO. 5115

CASAMBI PWM dimmer 12-24V 4-channel max. 144W



to the product page



- PWM dimmer with 4 channels for 12V or 24V for convenient operation of lights via the CASAMBI app
- the dimmer is mounted between the non-dimmable 12-24 VDC control gear and the constant voltage product
- suitable for 1-color strips, COLORselect strips, RGB and RGBW strips
- the max. output current is 6A, this can be freely distributed to channels 1-4
- protected against: overload, overcurrent and short circuit
- various pre-installed profiles can be selected in the CASAMBI app
- compatible with sensor (item no. 5117), radio remote control (item no. 5120) and wall switch (item no. 5121)
- Complete control via CASAMBI app:
- Control of brightness and light color
- Configuration of luminaires and luminaire networks
- Creating scenes and animations (color gradients)
- Intelligent timer and gallery functions

PRODUCT GROUP	EC002924...Steuergerät für Leuchten	PROTECTION CLASS (IP)	IP20
SUCCESSION ARTICLE	-	OUTPUT VOLTAGE	12 - 24 DC
WEIGHT IN KG	0.023	WARRANTY IN YEARS	2
POWER CONSUMPTION IN WATTS	max. 144 bei 24V	SUITABLE FOR MOUNTING	No
		COMPATIBLE WITH CASAMBI	Yes
		COMPATIBLE WITH APPLE HOMEKIT	No
		COMPATIBLE WITH GOOGLE ASSISTANT	No
		COMPATIBLE WITH AMAZON ALEXA	No
Dimensions		BEG FUNDING	Only relevant in Germany
length: 73mm		ELDAS-NR.	941010449
width: 30mm		DIAMETER IN MM	0
height: 18mm		ABMESSUNGEN BREITE MM	30
		ABMESSUNGEN HöHE MM	18