


PRODUCT NO. 3138-1

**LED power supply unit CC 13-30W 500-700mA 26-42V dimmable Phase cut-off/cut-on**



to the product page

- The power supply unit is dimmable via trailing-edge phase-cut dimmer or leading-edge phase-cut dimmer
- With constant current technology (CC), it is suitable for luminaires with constant current
- The connected constant current luminaires can be dimmed between 10%-100%
- Suitable dimmers: JUNG 1224 LED UDE, Eltako EUD61NPL-230V, GIRA Mini2440 00 and many more.
- The output current is adjustable: 500/550/600/700mA
- The power supply unit is set to 500mA as standard

**PRODUCT GROUP** EC002710\_LED-Betriebsgerät

**SUCCESSION ARTICLE** -  
**PREDECESSOR ARTICLE** 3138 3139

**WEIGHT IN KG** 0.134  
**POWER CONSUMPTION IN WATTS** 13-30

**Dimensions**

**length:** 138mm  
**width:** 44mm  
**height:** 30mm

<b>PROTECTION CLASS (IP)</b>	IP20
<b>INPUT VOLTAGE</b>	220 - 240 AC
<b>INRUSH CURRENT IN A</b>	0
<b>TC TEMPERATURE IN °C</b>	85
<b>PROTECTION CLASS</b>	II
<b>OVERVOLTAGE PROTECTION</b>	1000 V
<b>OUTPUT VOLTAGE</b>	26 - 42 DC
<b>INPUT VOLTAGE SPAN</b>	198-264 AC
<b>WARRANTY IN YEARS</b>	5
<b>INPUT VOLTAGE RANGE LUMINAIRE</b>	198-264 AC
<b>DIMMING MAINS VOLTAGE MODULATION</b>	Yes
<b>DIMMING PHASE CUT-OFF</b>	Yes
<b>NO DIM FUNCTION</b>	No
<b>COMPATIBLE WITH CASAMBI</b>	No
<b>COMPATIBLE WITH APPLE HOMEKIT</b>	No
<b>COMPATIBLE WITH GOOGLE ASSISTANT</b>	No
<b>COMPATIBLE WITH AMAZON ALEXA</b>	No
<b>DIMMING PHASE CUT-ON</b>	Yes
<b>PULSE DURATION IN µS</b>	0
<b>BEG FUNDING</b>	Only relevant in Germany
<b>ELDAS-NR.</b>	941934309
Dimension Length in mm	
<b>DIAMETER IN MM</b>	0

**ABMESSUNGEN BREITE MM**

44

**ABMESSUNGEN HÖHE MM**

30

Ausgangsstrom in A